



[10191/1888]

METHOD AND DEVICE FOR DETECTING A FAULT CURRENT ACROSS A
PIEZOELECTRIC ACTUATOR OF AN INJECTOR OR ITS HIGH VOLTAGE
SUPPLY LEAD

Background Information

The present invention relates to a method and a device for
detecting a fault current across a piezoelectric actuator of
an injector or its high voltage supply lead, according to the
definition of the species of the main claim. In known methods,
piezoelectric actuators are charged using a voltage of up to
several hundred volts, for example to 200 volts, to control
the switching valve or the nozzle needle of an injector. For
service personnel this high voltage may represent a hazardous
voltage source that can lead to electric shock upon direct
contact with current-carrying parts or the supply lead. For
example, during contact with the supply lead, a short circuit
to ground can result in a current of an order of magnitude of
200 mA. Applicable safety regulations, such as VDE¹ 100, allow
such a current for only a limited duration in order to prevent
hazardous ventricular fibrillation. The measurement and
detection of a fault current is not a simple matter, however,
because in comparison the useful current of 20 to 30 A is
several orders of magnitude higher, thus making the fault
current difficult to detect.

Summary of the Invention

The method and the device according to the present invention
for detecting a fault current across a piezoelectric actuator
of an injector or its high voltage supply lead, having the

¹Translator's note: Verband Deutscher Elektrotechniker (Association
of German Electrical Engineers)

RECEIVED
MAY - 2 2003
TECHNOLOGY CENTER 280

characterizing features of the independent Claims 1 and 11, in contrast, has the advantage that, by monitoring the voltage or the variation thereof across the charged actuator, even the relatively small fault current can be detected and protective measures can be effectively undertaken.

Advantageous developments of and improvements in the method described in the main claim derive from the measures represented in the subclaims. It is particularly advantageous that, in a fault scenario, a determined fault is weighted by a fault algorithm. Measurement errors or malfunctions, for example, are thus effectively suppressed, and only faults that actually occur are evaluated as such.

Furthermore, when an actual fault occurs, it is advantageous to shut off the voltage supply and also to discharge the actuator so rapidly that no contact hazard arises. In such a manner maximum protection is achieved and the danger of injury is largely avoided.

In a simple and particularly advantageous procedure, the voltage is determined at the beginning and at the end of the injection pause. Because the injection pause can last only several milliseconds, for example 2 ms, with the charged actuator, significant discharge of the actuator occurs during a short circuit.

For a system with multiple injection, it is also advantageous to perform voltage monitoring for individual injection pulses. The fault event can thus be detected early.

Since a plurality of actuators is generally supplied with high voltage from the power supply, it is advantageous to disconnect all actuators to increase safety.

Furthermore, it is advantageous to design the fault diagnosis in the form of a software program, since such a program can be

created relatively easily. In addition, revisions can be made more readily.

The software program for fault diagnosis is advantageously
5 incorporated into the control program for the actuator,
thereby eliminating the need for additional hardware.

Brief Description of the Drawings

10 An exemplary embodiment of the invention is depicted in the
drawing and explained in more detail in the following
descriptions.

Figure 1 shows a block circuit diagram,
15 Figure 2 shows a flow chart,
Figure 3 shows a voltage diagram, and
Figure 4 shows a flow chart for fault weighting.

Description of the Exemplary Embodiment

20 Figure 1 schematically shows a circuit diagram. A voltage
source 1, connected to two first switches 3a, 3b that are
connected in series, delivers the current or voltage for
charging a piezoactuator 5. An inductor 14 is connected
25 between switches 3a and 3b whose second terminal is connected
to a terminal of piezoactuator 5 via a cable harness 6 and a
plug connector 7. A second terminal of piezoactuator 5 is
connected to a second switch 4 via a plug connector 8 and
cable harness 6a, the return line of the second switch being
30 connected to the return line of voltage source 1 (ground
wire). Voltage source 1 as well as switches 3a, 3b, and 4 are
connected to a control device 2 via control lines 11a, 11b,
12, and 13. Switches 3a, 3b, and 4 are preferably designed as
semiconductor switches that transmit a high current and that
35 also have high electric strength against the high charging
voltage, which can be 200 volts or greater, depending on the
type of actuator. Diodes are connected antiparallel to

switches 3a, 3b, and 4 to allow a current to flow in the opposite direction.

5 It is customary to connect additional piezoactuators 5 in parallel to first switches 3a, 3b to form a bank. These piezoactuators have been omitted for clarity. If a plurality of actuators is interconnected to form a bank, second switch 4 is connected in series to each actuator 5 to enable the associated actuator 5 to be triggered. In this case, control
10 device 2 switches second switch 4 to transmission or blocking mode, thereby allowing the actuator to charge or discharge, respectively.

15 The current flow can be controlled using first switches 3a, 3b. To this end, control device 2 sets first switches 3a, 3b to transmission mode or blocks them.

20 Control device 2 also includes a measurement unit 9 that measures the voltage, the voltage variation, or a change in voltage, for example, to plug connectors 7 and 8, to actuator 5, and/or to cable harness 6, 6a. The controller 2 also includes a computer 10 that contains all required components and is controlled by a corresponding software program.

25 The dotted line to plug connector 7 with resistor R_m represents a leakage resistance that could occur, for example, upon contact by a person. In an injection pause, for example, when piezoactuator 5 is charged, measurement unit 9 detects the voltage of piezoactuator 5 at plug connector 7 such that the
30 voltage can be evaluated by control device 2. If first switches 3a, 3b, for example, are blocked, piezoactuator 5 discharges through leakage resistor R_m fairly rapidly since leakage resistor R_m has a relatively low resistance. A capacitance of 6 μF , for example, for piezoactuator 5 and an
35 assumed leakage resistance R_m of 1K ohm results in a time constant of approximately 6 ms. This means that in an injection pause of 2 milliseconds for a double-switching

control valve, for example, actuator 5 is discharged by up to 60 volts. The voltage is preferably measured at the end of the injection pause. It is not necessary to measure at the beginning of the injection pause because at that point actuator 5 was charged to the setpoint voltage specified by control device 2. From these two values, the voltage difference dU is determined after each charging process and compared to a predefined threshold value S . If the voltage difference dU lies below the predefined threshold value S , which for example can be established empirically, it can be concluded that no significant leakage current, which can be formed by the human body resistance R_m , is present. On the other hand, if the voltage difference dU exceeds the predefined threshold value S , a fault message is produced, voltage source 1 is shut off as promptly as possible, and/or piezoactuator 5 is discharged. This takes place with the assistance of switches 3a, 3b, and 4. Hazard from contact with parts conducting high voltage is thereby advantageously avoided.

As an alternative means of blanking out measurement errors or fault signals, the measured fault voltage is weighted with a predefined algorithm before a final fault is identified. This method will be described hereinafter in more detail, with reference to Figure 4.

In an alternative embodiment of the present invention, the voltage variation is also measured at the beginning of the injection pause or at intervals, and is evaluated with respect to the predefined threshold value S .

The mode of operation of the method is described in more detail, with reference to Figures 2 through 4. In the flow chart of Figure 2, the actuator voltage U_a is first measured in step 21 at plug connector 7, for example, while the actuator is triggered. In step 22, the measured actuator voltage U_a is tested for plausibility. This procedure will be

described hereinafter in more detail, with reference to Figure 3. Fault debouncing according to Figure 4 is performed in step 23, and the fault paths are updated in step 24.

5 Figure 3 shows a typical voltage diagram for a multiple injection, where a first voltage pulse A for a pilot injection and a multistage voltage pulse for a main injection B are represented over the time axis t . During pilot injection A, the voltage ceiling of the predefined voltage U_a runs
10 essentially horizontally, so that in this case no voltage deviation dU is present within the measurement phase. Thus, the thresholds S shown are not exceeded. In contrast, during main injection B the upper ceiling of voltage U_a drops with a difference dU . Depending on the magnitude of threshold S , a
15 leakage resistance R_m is indicated, which taking the weighting into consideration, can potentially lead to the fault message.

Figure 4 shows a flow chart for the detection and weighting of fault conditions, i.e., fault debouncing. A simple counting
20 algorithm is provided for weighting. In principle, each fault that occurs, i.e., all voltage differences dU above threshold S are summed up, and all values below threshold S are subtracted. A fault value is thus continuously obtained that is increased or decreased with each successive measurement.
25 Only when multiple faults are measured in succession and a predefined, applicable threshold value, for example 5, is exceeded can it be assumed that a final fault (defect) is present that leads to the fault message and/or disconnection. This method is described below, with reference to Figure 4.
30 Starting from step 36, it is assumed that no fault is present and that the voltage difference dU lies within threshold S . If the actual voltage dU lies outside the tolerance band for threshold S , as shown by arrow 31, a preliminary defect is assumed in step 32. A debouncing counter is then started that
35 iteratively counts upward or downward with each measurement. At this point, the fault is still considered to be preliminarily defective. If the debouncing counter has reached

the applicable threshold value in step 34, then a final defect is present because the actual voltage has repeatedly been outside the tolerance band for threshold S. However, if the actual voltage (differential voltage dU) lies within the tolerance band, the fault in step 35 is considered to be preliminarily corrected. The debouncing counter positions itself on the value OK, since its value is smaller than that of the applicable threshold value. There is no fault condition below the threshold value, and the condition is finally corrected (step 36).